

LAN-XI Light 4-channel Data Acquisition Module Types 3676 and 3677

LAN-XI Light Types 3676 and 3677 are stand-alone, 4-channel 25.6 kHz data acquisition units that are designed to cover a wide range of sound and vibration real-time analysis applications.

As part of the renowned LAN-XI hardware platform, both modules offer quality, durability and reliability for low-channel-count measurement set-ups. Their rugged design makes them well-suited for use in the field, as well as the lab.

The analogue input channels cover signals with frequencies from DC to 25 kHz, which is ideal for many NVH applications. They support direct voltage signals and transducers with TEDS (transducer electronic data sheet). They also provide conditioning for CCLD transducers such as microphones, accelerometers, binaural recording headsets and Sound Quality HATS.

Type 3676 includes Front Panel UA-2100-040, which has:

- Four input channels with BNC connectors

Other front panels cannot be used with the Type 3676 module.

Type 3677 includes Front Panel UA-3100-041, which has:

- Four input channels with BNC connectors
- One output channel with BNC connector with a frequency range: 0 to 25.6 kHz.

The output channel can be used as a high-quality signal generator to supply the signals necessary for performing system analysis in audio, electroacoustic and vibration test applications

You can detach Type 3677's standard front panel, UA-3100-041, and exchange it with optional Front Panel UA-3102-041 to support 200 V microphones requiring 7-pin LEMO connectors.

Uses and Features

Uses

As a data acquisition solution for NVH Simulator, Sonoscout™ and BK Connect®, LAN-XI Light provides real-time analysis for* :

- General sound and vibration measurements
- NVH (noise, vibration and harshness) recording and analysis
- Monitoring vehicle parameters
- Sound quality metrics (loudness, sharpness, articulation index)

* Please note, LAN-XI Light does not support PULSE™ LabShop and PULSE Time Data Recorder software applications



Type 3676





Type 3677
with optional front panel UA-3102-041

190062

Features

- DC to 25.6 kHz input range (sampling rate 65.5 kHz)
- Built-in constant current line drive (CCLD) to power sensors
- LAN interface
- LED indicators on each channel (conditioning, cable break)
- Power: Mains, DC, battery or PoE (IEEE 802.3af)
- Robust casing
- Generator (Type 3677 only):
 - One output channel with full generator functionality from 0 to 25.6 kHz
 - Can be set up using graphical tools of BK Connect. Control excitation type, frequency parameters, output level, level ramp up/down times, and burst excitation
 - Waveforms determined by software. BK Connect supports sine (fixed frequency), stepped sine, continuous and burst random, periodic and pseudo-random, white noise and user-defined waveforms

Compliance with Standards

   	<p>The CE marking is the manufacturer's declaration that the product meets the requirements of the applicable EU directives</p> <p>RCM mark indicates compliance with applicable ACMA technical standards – that is, for telecommunications, radio communications, EMC and EME</p> <p>China RoHS mark indicates compliance with administrative measures on the control of pollution caused by electronic information products according to the Ministry of Information Industries of the People's Republic of China</p> <p>WEEE mark indicates compliance with the EU WEEE Directive</p>
Safety	EN/IEC 61010–1 and ANSI/UL 61010–1: Safety requirements for electrical equipment for measurement, control and laboratory use
EMC Emission	EN/IEC 61000–6–4: Generic emission standard for industrial environments EN/IEC 61000–6–3: Generic emission standard for residential, commercial, and light-industrial environments CISPR 22: Radio disturbance characteristics of information technology equipment. Class B Limits
EMC Immunity	EN/IEC 61000–6–1: Generic standards – Immunity for residential, commercial and light industrial environments EN/IEC 61000–6–2: Generic standards – Immunity for industrial environments EN/IEC 61326: Electrical equipment for measurement, control and laboratory use – EMC requirements NOTE: The above is only guaranteed using accessories listed in this document
Temperature	IEC 60068–2–1 & IEC 60068–2–2: Environmental Testing. Cold and Dry Heat Ambient Operating Temperature: –10 to +55 °C (14 to 131 °F) Storage Temperature: –25 to +70 °C (–13 to +158 °F)
Humidity	IEC 60068–2–78: Damp Heat: 93% RH (non-condensing at 40 °C (104 °F))
Mechanical (non-operating)	IEC 60068–2–6: Vibration: 0.3 mm, 2 g, 10 – 500 Hz IEC 60068–2–27: Shock: 100 g IEC 60068–2–29: Bump: 1000 bumps at 25 g
Enclosure	IEC 60529: Protection provided by enclosures: IP 31

Specifications – LAN-XI Light Stand-alone Data Acquisition Module (25.6 kHz) Types 3676 and 3677

POWER REQUIREMENTS

DC Input: 10 – 32 V DC

Connector: LEMO, FFA.00.113, ground on shield

Power Consumption:

- **DC Input:** <15 W
 - **Typical Operating Time on Battery Type 2831-A:** > 7 hours
 - **Supply via PoE:** According to IEEE 802.3af, max. cable length 100 m
- Temperature Protection:** Temperature sensor limits module's internal temperature to 80 °C (176 °F). If temperature exceeds limit, system will shut down the module

ANALOGUE INPUT CHANNELS

Frequency Range		DC to 25.6 kHz or any range defined by high-pass filters and by software decimation set under 'frequency span'
Sampling Rate		65.5 k samples/s
A/D Conversion		24 bit
Data Transfer		24 bit
Input Voltage Ranges	Type 3676	1 – 10 V _{peak}
	Type 3677	0.25 – 10 V _{peak}
Input Signal Coupling	Differential	Signal Ground is 'Floating' (1 MΩ re chassis)
	Single-ended	Signal ground is connected to chassis ('Grounded')
Input Impedance		Direct: 1 MΩ <300 pF CCLD: >100 kΩ <300 pF
Absolute Maximum Input		±60 V _{peak} without damage

LAN

Connector type RJ45

DIMENSIONS AND WEIGHT

Height: 132.6 mm (5.22")

Width: 27.5 mm (1.08")

Depth: 248 mm (9.76")

Weight: 750 g (1.65 lb)

High-pass Filters		-0.1 dB *	-10% @ **	-3 dB @ **	Slope
* Defined as the lower frequency, f_L , for guaranteed fulfilment of -0.1 dB accuracy ** Defined as the nominal -10%/-3 dB filter frequency *** Single analogue pole and 2nd order digital filter section	0.1 Hz -10% digital high-pass filter	0.5 Hz	0.1 Hz	0.05 Hz	-20 dB/dec.
	0.7 Hz -0.1 dB digital high-pass filter	0.7 Hz	0.15 Hz	0.073 Hz	
	1 Hz -10% analogue high-pass filter	5 Hz	1.0 Hz	0.5 Hz	-20 dB/dec.
	7 Hz -0.1 dB digital high-pass filter	7 Hz	1.45 Hz	0.707 Hz	
	22.4 Hz -0.1 dB analogue*** high-pass filter	22.4 Hz	14.64 Hz	11.5 Hz	-60 dB/dec.
Intensity filter (analogue)		112 Hz	23.00 Hz	11.2 Hz	-20 dB/dec.
Absolute Amplitude Precision, 1 kHz, 1 V_{input}			±0.05 dB, typ. ±0.01 dB		
Amplitude Linearity (linearity in one range)			±0.1 dB, typ. ±0.01 dB		
0 to 60 dB below full scale			±0.1 dB, typ. ±0.01 dB		
60 to 80 dB below full scale			±0.2 dB, typ. ±0.02 dB		
80 to 100 dB below full scale			typ. ±0.05 dB		
Overall Frequency Response, re 1 kHz, from lower limit f_L to upper limit f_U f_L is defined as the lower frequency for guaranteed fulfilment of -0.1 dB accuracy (see High-pass Filters) f_U is defined as the chosen frequency span			±0.1 dB		
Noise:	Input Range	Guaranteed	Typical		
Measured lin. 10 Hz to 25.6 kHz (Input terminated by 50 Ω or less)	0.25 V _{peak} (Type 3677) or 1 V _{peak} (Type 3676)	< 7.5 μV _{rms} (< 47 nV _{rms} /√Hz @ 1 kHz)	< 5.5 μV _{rms} (< 35 nV _{rms} /√Hz @ 1 kHz)		
	10 V _{peak}	< 75 μV _{rms} (< 470 nV _{rms} /√Hz @ 1 kHz)	< 55 μV _{rms} (< 350 nV _{rms} /√Hz @ 1 kHz)		
Spurious-free Dynamic Range re full-scale input (Input terminated by 50 Ω or less) Spurious-free dynamic range is defined as the ratio of the rms full-scale amplitude to the rms value of the peak non-harmonic spectral component	Input Range	Typical			
	0.25 V _{peak} (Type 3677) or 1 V _{peak} (Type 3676)	130 dB			
	10 V _{peak}	130 dB 120 dB with DC coupling			
DC Offset re Full Scale Measured after automatic DC compensation at current temperature when changing from AC to DC coupling or changing input range when DC coupled		Guaranteed	Typical		
		< -80 dB	< -90 dB		
Harmonic Distortion (all harmonics)		Guaranteed	Typical		
		-80 dB in 0.25 V (Type3677) or 1 V (Type 3676) range -75 dB in 10 V range	-100 dB @ 1 kHz		
Crosstalk: Between any two channels	Frequency Range	Guaranteed	Typical		
	0 - 25.6 kHz	< -80 dB	-100 dB		
Channel-to-Channel Match Input ranges: • 10 V _{peak} • 0.25 V _{peak} (Type 3677) • 1 V _{peak} (Type 3676)		Guaranteed	Typical		
Maximum Gain Difference f_L is defined as the -0.1 dB filter frequency		0.2 dB from lower frequency limit, f_L , to 25.6 kHz (0.4 dB at -10% filter frequency)		±0.05 dB	
Maximum Phase Difference f_L is defined as the -0.1 dB filter frequency					

180162

Common Mode Rejection		Guaranteed	Typical
	0.1 – 120 Hz	60 dB	65 dB
	120 Hz – 1 kHz	50 dB	55 dB
	1 kHz – 25.6 kHz	30 dB	40 dB
Absolute Max. Common Mode Voltage		±5 V _{peak} without damage	
		±3 V _{peak} without clipping	
		If common mode voltage exceeds the max. value, care must be taken to limit the signal ground current in order to prevent damage. Maximum is 100 mA. The instrument will limit the voltage to the stated max. 'without damage' common mode value	
Anti-aliasing Filter	Filter Type	3rd order Butterworth	
At least 90 dB attenuation of those frequencies that can cause aliasing	-0.1 dB @	25.6 kHz	
	-3 dB @	64 kHz	
	Slope	-18 dB/octave	
Supply for Microphone Preampifiers (Type 3677 only)		±14.0 V, max. 100 mA per channel (max. 100 mA total/module)	
Supply for Microphone Polarization (Type 3677 with UA-3102-041 only)		200 V ±1 V, or 0 V (set per channel)	
Supply for CCLD		3.6 mA from 24 V source	
		If any CCLD-coupled channel is paralleled with another channel, this must also be CCLD-coupled. Otherwise the signal might be clipped by the paralleled channel	
Tacho Supply		CCLD for Type 2981 (Power supply for legacy types MM-0012 and MM-0024 not available)	
Analogue Special Functions		Transducers: Supports IEEE 1451.4-capable transducers with standardized TEDS	
Overload Detection		Signal Overload: Detection level in 0.25 V range: ±0.25 V _{peak} ; in 10 V range: ±10 V _{peak} (in CCLD mode: ±7 V _{peak}) CCLD Overload: Detection of cable break or short-circuit + detection of CCLD transducer working point fault. Detection level: +2 V/20 V Microphone Preampifier Overload: Detection of microphone preampifier current consumption too high or too low. Detection level default is 10 mA/1 mA. Adjustable detection level of 1 to 20 mA, or 100 mA if disabled Common Mode Voltage Overload: Detection level: ±3 V	
Protection		If signal input level exceeds the measuring range significantly, the input will go into protection mode until the signal goes beyond the detection level again – but at least for 0.5 s. While in protection mode, the input is partly switched off and the input impedance is strongly increased. (The measured value will be strongly attenuated but still detectable) Direct mode detection level: ±33 V _{peak} CCLD mode detection level: +27/-2 V _{peak}	

OUTPUT CHANNEL (TYPE 3677 ONLY)

Output Connector	1 × BNC
Output Coupling	DC
Signal Ground Coupling	Floating or grounded to chassis
D/A Conversion	24 bit
DC Offset (DC Value set to 0 V)	≤1 mV auto-adjusted by loopback (<-80 dB re full scale)
Output Voltage Range (DC)	0 to ±10 V ±0.5% of requested value
Output Voltage Range (AC)	10 μV _{peak} – 10 V _{peak}
Output Impedance	50 Ω
Output Load	Max. 40 mA _{peak}
Frequency Range	0 – 25.6 kHz
Frequency Response re 1 kHz	±0.1 dB, 1 mHz to 25.6 kHz
Frequency Accuracy	0.00025%
Frequency Resolution	1 mHz (defined in BK Connect)
Phase Resolution	100 mdegrees (defined in BK Connect)
Phase Deviation Between Channels	<20 mdegrees for frequencies below 1 kHz
Waveform	Software-determined arbitrary waveforms up to 2 Msamples Waveforms available in BK Connect: Single fixed sine (continuous), stepped sine, random (continuous or burst), pseudo-random, periodic random. User-defined, arbitrary waveforms up to 25.6 kHz can be streamed or downloaded

Amplitude Linearity @ 1 kHz		Guaranteed	Typical
		± 0.1 dB	0 – 100 dB below $7 V_{rms}$
Noise μV_{rms} (nV/ \sqrt{Hz}) in 50 kHz bandwidth	up to $316 V_{peak}$	Guaranteed $1 \mu V_{rms}$ (4.4 nV/ \sqrt{Hz})	Typical $0.5 \mu V_{rms}$ (2.2 nV/ \sqrt{Hz})
	up to $10 V_{peak}$	$10 \mu V_{rms}$ (44 nV/ \sqrt{Hz})	$5 \mu V_{rms}$ (22 nV/ \sqrt{Hz})
Harmonic Distortion Products	0 – 25.6 kHz	< -80 dB re full range output	
Spurious In Band (non-harmonic)	0 – 25.6 kHz	< -100 dB re full range output or 1 μV , whichever is greater	
Spurious Out of Band (non-harmonic)	Up to 1 MHz	< -80 dB re full range output	
Absolute Amplitude Precision		Guaranteed	
@ 23 °C, 1 kHz, $1 V_{rms}$		± 0.05 dB	
Crosstalk Between output channels and between any output channel and any input channel terminated by less than 50 Ω (unloaded generator output)	0 – 25.6 kHz	Guaranteed	Typical
		-120 dB	-130 dB
Common Mode Rejection		Guaranteed	
1 Hz – 1 kHz		60 dB	
Maximum Common Mode Voltage		5 V_{peak} , DC – 80 MHz	
		If common mode voltage exceeds the max. value, care must be taken to limit the signal ground current in order to prevent damage. Max. is 100 mA. The instrument will limit the voltage to the stated max. "without damage" common mode value	
Reconstruction Filter		Sixth order Butterworth (-3 dB frequency = 120 kHz typically)	
Attenuation of Mirror Frequencies		> 80 dB	
Overload Detection		Reported to BK Connect; indicated by light rings on output connectors for output voltage above $11 V_{peak}$ and output current above $40 mA_{peak}$	

Type 3676-B-040 LAN-XI Light 4-ch. Stand-alone Input Module, 25.6 kHz

Includes the following accessories:

- UA-2100-040: Detachable front panel with 4 × BNC input connectors
- ZG-0426: Power supply via mains (100 – 240 V)
- AO-1450: LAN Cable, shielded CAT 6, RJ 45 (M), 2 m (6.5 ft)

Type 3677-A-041 LAN-XI Light 4+1-ch. Stand-alone Input/Output Module, 25.6 kHz

Includes the following accessories:

- UA-3100-041: Detachable front panel with 4 × BNC input connectors and 1 × BNC generator output
- ZG-0426: Power supply via mains (100 – 240 V)
- AO-1450: LAN Cable, shielded CAT 6, RJ 45 (M), 2 m (6.5 ft)

Calibration Services for Data Acquisition Modules

ANA-LNXI-CAF	Accredited Calibration
ANA-LNXI-CAI	Initial Accredited Calibration
ANA-LNXI-CTF	Traceable Calibration
ANA-LNXI-TCF	Conformance Test with Certificate

Supported Brüel & Kjær Products

CABLING AND ADAPTERS

AO-0087-x-yyy [*]	Cable, coax single screen, BNC (M) to BNC (M), max. +85 °C (+185 °F)
AO-0414-x-yyy [*]	Cable, 7-pin LEMO (1B F) to 7-pin LEMO (1B M), max. +80 °C (+176 °F)
AO-0479-x-yyy [*]	Cable, 7-pin LEMO (1B M) to BNC (M) max. +80 °C (+176 °F)
AO-0531-x-yyy [*]	Cable, coax, 10–32 UNF (M) to BNC (M), max. +80 °C (+176 °F)
JJ-0152	Adapter, T-shaped BNC (M) to dual BNC (F)
JP-0145	Adapter, BNC (M) to 10–32 UNF (F), straight

LAN-XI PLATFORM OPTIONS AND ACCESSORIES

Type 2831-A	Battery Module
UA-3102-041	Front panel with 4 × LEMO input connectors and 1 × BNC output (for Type 3677 only)
Type 3660-A-20x [†]	Wireless LAN Frame
ZG-0858	DC Power Charger, car utility connector to Type 2831-A
AO-0546	DC Power Cable, car utility connector to single module
BZ-7848-A	LAN-XI Notar™, stand-alone recorder licence

SENSORS

A wide range of Brüel & Kjær accelerometers, microphones, preamplifiers and sound intensity probes is available for use with a LAN-XI-based systems. The system supports IEEE 1451.4-capable transducers with standardized TEDS. Visit bksv.com/transducers for more information

SOFTWARE

BK Connect software applications and applets support the entire LAN-XI platform, including LAN-XI Light. See the individual product data for limitations and requirements. For more information on this software platform, visit bksv.com/bkconnect.

Sonoscout NVH Recorder BZ-5950 supports selected products in the LAN-XI platform, including LAN-XI Light. See product data [BP 2463](#) for details.

* x = D (decimetres) or M (metres); yyy = length in decimetres or metres.

Please specify cable length when ordering

† Where x = 0 or 1. Type 3660-A-200 is for international use (except Japan), Type 3660-A-201 is for use in Japan only.

Brüel & Kjær and all other trademarks, service marks, trade names, logos and product names are the property of Brüel & Kjær or a third-party company.

Brüel & Kjær Sound & Vibration Measurement A/S
 DK-2850 Nærum · Denmark · Telephone: +45 77 41 20 00 · Fax: +45 45 80 14 05
www.bksv.com · info@bksv.com
 Local representatives and service organizations worldwide

Although reasonable care has been taken to ensure the information in this document is accurate, nothing herein can be construed to imply representation or warranty as to its accuracy, currency or completeness, nor is it intended to form the basis of any contract. Content is subject to change without notice – contact Brüel & Kjær for the latest version of this document.

